



Wiring scheme for
22 pin DIL to QFN20

QFN20

DIL22	QFN20
1	Bottom pad
2	1
3	2
...	...
21	20
22	Bottom pad

TOP VIEW

SIDE VIEW

BOTTOM VIEW

Dimension	Millimeters			Dimension	Millimeters		
	Min	Nom	Max		Min	Nom	Max
A	0.80	0.90	1.00	E	4.00 BSC.		
A1	0.03	0.07	0.11	E2	2.55	2.70	2.85
A3	0.25 REF			L	0.30	0.40	0.50
b	0.18	0.25	0.30	aaa	—	—	0.15
D	4.00 BSC.			bbb	—	—	0.10
D2	2.55	2.70	2.85	ddd	—	—	0.05
e	0.50 BSC.			eee	—	—	0.08